Check if your Telstra GO Repeater is configured to boost 4G signals



Telstra GO (G31) Repeater



Telstra GO G41 Stationary Repeater



Telstra GO ROAM R41 Mobile Repeater

- Telstra GO Repeaters (GO G31, GO G41, GO ROAM R41) operate on both 3G and 4G and will not be impacted when 3G closes on 31 August 2024.
- However, in some instances they may have been configured to only operate on 3G.
- We encourage you to check your GO Repeater settings, using a smartphone with the Cel-Fi WAVE app installed to see if its correctly configured to boost 4G signals.
- Instructions to check your GO Repeater settings:
 - Download the Cel-Fi WAVE app available from the Google Play Store or Apple App Store on your smartphone.
 - Open the WAVE app on your smartphone and ensure you are in close proximity to your GO Repeater to allow it to connect through bluetooth.
 - Follow instructions to
 - Check your GO Repeater in the Cel-Fi WAVE app using a smartphone. Tap on Settings > Band Settings > Under Technology, select 4G if it isnt already selected.
 - Congratulations your GO Repeater will now be configured to boost 4G signals.



			@
DASHBOARD	SETTINGS	ADVA	NCED
Booster Name			~
Software Version			~
ntenna Settings			~
اا، Band Settir	ngs		^
Booster Mode:	O Mobile		
	Stationary		
Technology:	0	Auto	
	0	3G	
		4G	
Bands:		Band 3	
		Band 5	
	0	Band 28	
ا ان Channel Se	ttings		~